1. Basic Diagnostic Procedure

A: PROCEDURE

	Step	Check	Yes	No
2	PERFORM CUSTOMER INTERVIEW. Using the Check List for Interview, ask the customer the condition of how the trouble occurred. <ref. al(diag)-3,="" check="" check,="" for="" interview.="" list="" to=""> CHECK LAN SYSTEM.</ref.>	Did you interview the customer? Is there any fault?	Go to step 2. Perform the	Interview the customer. <ref. al(diag)-3,="" check="" check,="" for="" interview.="" list="" to=""> Go to step 3.</ref.>
_	Inspect LAN system. <ref. basic="" diagnostic="" lan(diag)-2,="" procedure,="" procedure.="" to=""></ref.>	is there any laute.	inspection according to the diagnosis for LAN system.	do to step o .
3	CHECK AUTO HEADLIGHT BEAM LEVELER SYSTEM. Using the Subaru Select Monitor, read DTC of the auto headlight beam leveler system inspection. <ref. (dtc).="" al(diag)-10,="" code="" diagnostic="" operation,="" read="" to="" trouble=""> NOTE: If the communication function of the Subaru Select Monitor cannot be executed properly, check the communication circuit. <ref. al(diag)-8,="" communication="" for="" impossible,="" initializing="" inspection,="" monitor.="" select="" subaru="" to=""></ref.></ref.>		Perform the diagnosis according to DTC. <ref. (dtc).="" al(diag)-13,="" code="" diagnostic="" list="" list,="" of="" to="" trouble=""></ref.>	Go to step 4.
4	CHECK DIAGNOSTICS WITH PHENOME- NON. Check "Diagnostics with Phenomenon". <ref. to AL(diag)-18, Diagnostics with Phenome- non.></ref. 	Does the symptom apply?	Perform diagnosis according to the procedures in the diagnostics with phenomenon.	Go to step 5.
5	CHECK TROUBLE PHENOMENON. 1) Perform the basic inspection and function check. <ref. al(diag)-4,="" description.="" general="" inspection,="" to=""> 2) Check the auto headlight beam leveler CM. <ref. al(diag)-6,="" control="" i="" module="" o="" signal.="" to=""> 3) Perform check of current data. <ref. al(diag)-12,="" current="" data.="" read="" to=""> 4) Perform a unit check.</ref.></ref.></ref.>	Was the trouble cause found?	Repair or replace the cause of trou- ble.	System is normal.