

POWER BACK DOOR CLOSER SWITCH

INSPECTION

1. INSPECT POWER BACK DOOR CLOSER SWITCH ASSEMBLY

- (a) Measure the resistance according to the value(s) in the table below.

Standard resistance

Tester Connection	Switch Position	Specified Condition
1 - 2	Pushed (ON)	Below 1 Ω
1 - 2	Free (OFF)	10 k Ω or higher

