

28. Any speaker does not work.

INSPECTION PROCEDURE

1 Is radio operating normally?

YES

Radio assembly faulty.

NO

2 Is hiss noise produced by non-functioning speaker.

YES

Radio assembly faulty.
Recheck system after repair.

NO

3 Does continuity exist in speaker wire harness?

NO

Speaker wire harness faulty.

YES

4 Temporarily install another speaker. Function OK?

YES

Speaker faulty.

NO

Power amplifier faulty.
Recheck system after repair.