

PROBLEM SYMPTOMS TABLE

Proceed to the reference page shown in the matrix chart below for each malfunction symptom and trouble-shoot for each circuit.

HINT:

Troubleshooting of the theft deterrent system is based on the premise that the door lock control system is operating normally. Accordingly, before troubleshooting the theft deterrent system, first make certain that the door lock control system is operating normally.

Details of Problem			Inspecting Circuit*1	See page
The theft deterrent system cannot be set			1. Indicator light circuit	DI-695
			2. ECU power source circuit	DI-697
			3. Key unlock warning switch circuit	DI-710
			4. Door key lock and unlock switch circuit	DI-714
			5. Door courtesy switch circuit	DI-718
			6. Door unlock detection switch circuit	DI-716
			7. Engine hood courtesy switch circuit	DI-720
The indicator light does not blink when system is set			Indicator light circuit	DI-695
When the system is set	When the rear door is unlocked	The system does not operate	Door unlock detection switch circuit	DI-716
	When the engine hood is opened		Engine hood courtesy switch circuit	DI-720
While the system is in warning operation		Horns do not sound	Horn relay circuit	DI-702
		Theft deterrent horn does not sound	Theft deterrent horn circuit	DI-700
		Headlights do not flash	Headlight control relay circuit	DI-704
		Taillights do not flash	Taillight control relay circuit	DI-706
		The door lock is not locked	Door unlock detection switch circuit	DI-716
When the system is set	It is not canceled when the ignition key is turned to ACC or ON position		Ignition switch circuit	DI-708
System is still set even when a rear door is open			Door courtesy switch circuit	DI-718
Even when the system is not set		Horns sound	Horn relay circuit	DI-702
		Theft deterrent horn sounds	Theft deterrent horn circuit	DI-700
		Headlights stay on	Headlight control relay circuit	DI-704
		Taillights stay on	Taillight control relay circuit	DI-706

*1: If numbers are given to the circuit proceed with troubleshooting in the order indicated by those numbers.