


Power Source Circuit (Multi-Display Assembly)

CIRCUIT DESCRIPTION

This circuit is the power source circuit to operate the multi-display assembly.

WIRING DIAGRAM




C

I27360

INSPECTION PROCEDURE

- 1 Check voltage between terminals B1, ACC, IG and GND of multi-display assembly.**



- (a) Disconnect the connector from the multi-display assembly.
(b) Measure the voltage according to the value(s) in the table below.

Standard:


Tester connection	Condition	Specified condition
B1 – GND1	Always	10 to 14 V
ACC – GND1	Ignition SW ACC	10 to 14 V
IG – GND1	Ignition SW ON	10 to 14 V

OK

Proceed to next circuit inspection shown in problem symptoms table. (See page [DI-1595](#))

NG

- 2 Check continuity between terminal GND1 of multi-display assembly and body ground.**



- (a) Disconnect the connector from the multi-display assembly.
(b) Measure the resistance according to the value(s) in the table below.

Standard:

Tester connection	Condition	Specified condition
GND1 – Body ground	Always	Below 1 Ω

OK

Repair or replace harness or connector between navigation ECU and fuse.

NG

Repair or replace harness or connector between navigation ECU and body ground.