

## 2. Headlight and Tail Light System

### A: WIRING DIAGRAM

#### 1. HALOGEN TYPE HEADLIGHT

<Ref. to WI-129, WIRING DIAGRAM, Headlight System.>

#### 2. CLEARANCE LIGHT AND ILLUMINATION LIGHT

<Ref. to WI-135, WIRING DIAGRAM, Clearance Light and Illumination Light System.>


### B: INSPECTION

#### 1. HEADLIGHT SWITCH

<Ref. to LI-11, INSPECTION, Combination Switch (Light).>

#### 2. HEADLIGHT RELAY

Measure the headlight relay resistance between terminals when connecting terminal No. 4 to the battery positive terminal and terminal No. 3 to the battery ground terminal.




LI-00001

Continuity	Terminal No.	Standard
Yes	1 and 2	Less than 1 Ω
No		1 MΩ or more

### 3. TAIL AND ILLUMINATION RELAY

Measure the resistance between the tail and illumination relay terminals when connecting terminal No. 4 to the battery positive terminal and terminal No. 3 to the battery ground terminal.



LI-00001

Continuity	Terminal No.	Standard
Yes	1 and 2	Less than 1 Ω
No		1 MΩ or more